

SOCKET & SEE™

SOK34 Easy Socket and Earth Loop Tester



- Detect good plus 18 wiring fault conditions with fault locate
- Tests true earth loop impedance
- Earth loop results shown as Good / Check or Urgent Check
- New circuitry means no tripping RCD's
- Continuous tone gives fast indication of good wiring
- Warbling tone gives fast indication of faulty wiring
- Built in self check at beginning of test
- Gives clear indication even on noisy circuits
- Logical green for go indication
- Small and robust
- Simple to use

Description

The Socket and See SOK34 combines both socket tester functions and loop test in one device.

It's advanced circuitry means it won't trip RCD's. The SOK34 also performs a self check before each use to ensure the circuitry is in correct working order.

Loop test results are clearly indicated via LED's as either Good (green) Check (orange) or Urgent Check (red), alerting the user to any potential issues that need addressing. The loop test is carried out automatically when plugged in with no button to press.

The SOK34 detects good plus 18 wiring fault conditions. Green LED indication and a continuous tone quickly indicates good wiring. A warbling tone with orange or red LED indication indicates a wiring fault.

Small and robust, the SOK34 is design to fit into virtually any tool bag and be on hand for quick checks whilst on site.

Specification

Power Supply:	230V
Input current:	<18mA
Frequency:	50Hz
Temperature:	0 - 40°C
Humidity:	<95% non-condensing
Safety compliance:	BSEN 61010-1
Duty Cycle:	Non continuous, <2min

Socket & See Socket Testers

SOK22 Craftsman Socket Tester

SOK32 Professional Socket Tester

SOK34 Easy Socket & Earth Loop Tester

SOK36 Professional Socket / Earth Loop / Polarity / RCD Tester

Century Road,
High Carr Business Park,
Newcastle-Under-Lyme,
ST5 7UG
United Kingdom

www.socketandsee.co.uk
info@socketandsee.co.uk
Tel: 44 (0)1782 567096
Fax: 44 (0)1782 567095
Socket & See is a brand name of UK Test Instruments Limited

go test..